

Please read all the instructions carefully (including those who hate to read instructions!)



Key to illustration:

- | | | | |
|---|----------------------------|-----------------|-----------------------|
| 1 | Receiver cable, 3-pin: | | |
| | - = negative | black or brown | |
| | + = positive | red | |
| | p = pulse | white or orange | |
| 2 | Battery connection neg (-) | black | |
| 3 | Battery connectin pos. (+) | red | Reverse use: |
| 4 | Motor connection a | red | blue, black |
| 5 | Motor connection b | white, yellow | white, yellow |
| 6 | Motor connection c | blue, black | red |
| | | | Brushed motor: |
| | | | Motor + |
| | | | no connect. |
| | | | Motor - |

Please note the following guidelines, which apply when you are connecting the motor and reversing its direction of rotation:

- 1) The controller can be used with sensorless and sensor-controlled motors. If your motor is sensor-controlled, the 5-pin connector is not used.
- 2) The three motor cables can be connected in any order.
- 3) To reverse the direction of rotation you have to swap over two of the three motor cables; we recommend that you swap the two outer wires.

Unfortunately the colour coding of the motor windings may not apply consistently to the sensor-controlled and sensorless types.

Note: for right-hand rotation, Plettenberg motors should be connected as the colour code shows. Mostly **futures** should be connected with the cooling plate facing the outside of the fuselage.

Dear customer,

Congratulations on your choice of a **future** speed controller, which is a micro-computer controlled unit developed and manufactured entirely in Germany, designed for brushless and sensorless 3-phase rotary current motors.

All models of the **future** are amongst the world's smallest, lightest and most capable speed controllers.

The **ips** (intelligent programming system) which is a standard feature of the ...bo and ...be versions of the **future**, makes it as simple as possible to configure the controller to match any radio control system. The special versions designed for competition use have fixed, pre-set values to match the transmitter travels.

The **integral motor connector system** is a feature of all **future** controllers, and makes it possible to remove the unit for servicing, or for fitting in another model, simply by unplugging the cables - no soldering is required.

Contents

Chapter	Subject	Page
1	Warning notes, cautions	3
2	Ensuring safe, trouble free operation	4
3	Intended applications	5
4	Protective circuits	6
5	Monitor displays	7
6	Installing and connecting the unit	7
7	Legal matters	8
7.1	Warranty	8
7.2	Liability limits / compensation	8
7.3	CE certification	8
8	Connector systems and mounting instructions	9
9	Using the controller for the first time	11
9.1	ips - the intelligent programming system	11
9.2	Symbols and terminology	11
9.3.1	Normal operation - propeller brake mode	12
9.3.2	No - brake mode	13
9.3.3	Gearbox mode	14
9.3.4	future-__Fo, Po	15
9.3.5	future-58Ce, Co, Wo - car-mode	16
9.3.6	future-58Ce, Co, Wo - boat-mode	17
9.3.7	future-__Ho, He	18
9.3.8	Converesion to and from brushed motor mode !	7
10	Specifications	20

1 Warning notes, cautions

Electric motors fitted with propellers are dangerous and require proper care for safe operation. Keep well clear of the propeller at all times when the battery pack is connected.

Technical defects of an electrical or mechanical nature may result in unintended motor runs; loose parts may cause serious personal injury and/or property damage.

The CE-certificate on the speed controller does not absolve you from taking proper care when handling the system!

Speed controllers are exclusively for use in RC models. Their use in man-carrying aircraft is prohibited.

Speed controllers are not protected against reverse polarity (+ terminal and - terminal reversed). Connecting the **battery pack** to the **motor leads** of the controller will almost certainly cause irreparable damage.

Electronic equipment is sensitive to humidity. Speed controllers which have got wet may not function properly even after thorough drying. You should send them back to us for cleaning and testing.

Do not use speed controllers in conjunction with a power supply connected to the mains. Energy reversal can occur when the motor slows down and stops, and this may damage the power supply or cause an over-voltage condition which could damage the controller.

Never disconnect the flight pack while the motor is running, as this could cause damage on a speed controller.

Please take care when switching off the receiver battery: depending on the receiver you are using, it may send an incorrect throttle signal to the **future** at this moment, which could then cause the motor to burst into life unexpectedly.

If you are using a **future** with BEC system:

a) On no account connect a separate receiver battery or an electronic battery switch (two receiver batteries), as this may cause damage to the speed controller and could cause current to flow from the receiver battery to the motor.

b) If you want to use a separate receiver battery cut through the + wire in the receiver cable, or pull it out of the connector if possible. However, for greater protection against motor-induced interference it is always better to use a speed controller with an opto-coupler.

Protect the speed controller from mechanical loads, vibration, dirt and contamination.

Keep the cables to the motor as short as possible (max. length = 10 cm / 4").

Do not exceed the maximum stated length of cable between battery and **future** (max. length: 20 cm / 7...8"). The wiring inside the battery pack must also be as short as possible. Use in-line soldered "stick" packs.

For the same reason, use a clamp-type amperemeter, not a series meter with shunt resistor.

Never leave the flight battery connected when ...

... the model is not in use and/or

... the battery pack is being charged.

Although some speed controllers feature a separate On/Off switch, this does not isolate it completely from the battery.

Speed controllers can only function properly if they are in full working condition. The protective and monitoring circuits can also only work if the speed controller is in good operating condition.

In the case of motor failure (e.g. short circuits in the windings) the over-temperature sensor in the controllers may react too slowly to prevent damage. Switch the motor off immediately to prevent permanent damage to the speed controller.

Note: Please remember that the monitoring circuits are unable to detect every abnormal operating condition, such as a short between the motor cables. Note also that a stalled motor will only trip the current limiter if the motor's stall current is well above the controller's peak current. For example, if you are using an 80 A controller in conjunction with a 20 A motor, the current monitor will not detect an excessive current even when the motor is stalled.

2 Ensuring safe, trouble-free operation

Use only compatible connectors. A 2 mm pin cannot provide reliable contact in a 2.5 mm socket. The same applies with 2mm gold-contact pins and 2 mm tin-plated sockets.

Please also remember that ...

... the wiring of your RC-components must be checked regularly for loose wires, oxidation, or damaged insulation, especially when using a BEC system.

... your receiver and the aerial must be at least 3 cm (>1") away from motor, speed controller and high-current cables. For example, the magnetic fields around the high-current cables can cause interference to the receiver.

... all high-current cables must be as short as possible. Maximum length between flight pack and speed controller should not exceed 20 cm (7"), between speed controller and motor: 10 cm (4").

... all high-current cables longer than 5 cm (2") must be twisted together. This applies in particular to the motor power cables, which are very powerful sources of radiated interference.

... in model aircraft: half of the receiver aerial's length should be routed along the fuselage, the other half should be allowed to trail freely (take care not to tread on it). Do not attach the end of the aerial to the fin!

... in model boats: half of the receiver aerial's length should be deployed inside the hull above the waterline, the other half should be threaded into a small tube mounted upright.

Every time you intend to use the power system - before you turn on the receiver - make sure that ...

... no one else is using the same frequency (identical channel number).

... your transmitter is switched on and the

throttle stick is (as a rule) in the STOP position (exceptions see Section 9).

Carry out a range check before each flight. Ask an assistant to hold the model aircraft and set the throttle stick to the half throttle position. Collapse the transmitter aerial. Walk away from the model to the distance stated by the RC system manufacturer (this might be a distance of about 50-60 m = 200'). Make sure that you still have full control of the system at this range.

As a general rule: receiver interference is more likely to occur when using a controller with BEC system, as these units do not feature an opto-coupler with its optical link.

When Ni-Cd batteries approach the end of their charge, voltage falls drastically and quickly. The **future** detects this and reduces power to the motor automatically. This should leave sufficient energy to bring your model safely back home. However, if you use a small number of cells of high internal resistance and operate at high motor currents, the controller may reduce power before the pack is discharged. You can eliminate this problem by using low resistance straps to connect the cells, or use the direct cell-to-cell soldering technique ("sticks") and short, heavy-gauge wire if you assemble your own batteries.

Your receiver also benefits from the stability of the voltage supplied from the battery by a BEC system. If the BEC voltage is stable, the receiver is less liable to suffer interference.

The CE symbol is your guarantee that the unit meets all the relevant interference emission and rejection regulations when it is in use.

If you encounter problems operating the **future** controller, please note that many problems are due to an unsuitable combination of receiving system components, or an inadequate installation in the model.

Important note: Please switch on your transmitter before switching on your receiver. When receiving no transmitter signal some PCM-receiver give no servo-pulse to the output but a constant high voltage. This voltage will set the **future** after 5 seconds into the brush mode (see section 9.3.8). You can indicate this mode by the double-tone-beep when arming. Please switch back this mode in the same manner.

3 Intended applications:

Low voltage types:

future-18be: For motors up to 100g (Astro 020, Aveox 1005); range from 6 to 10 Ni-Cd/Ni-MH cells; BEC 5V/1,5A; *ips*.

future-25be: For softliners, small sport-models, small ducted fans; range from 6 - 10 Ni-Cd/Ni-MH cells; BEC 5V/1,5A; *ips*.

future-20He: Controller and constant speed regulator for helicopters with max. of 1 m rotor-diameter. 6-8 Ni-Cd/Ni-MH cells; cooling fins; BEC 5V/1,5A.

future-45bo: This controller is primarily designed for use in electric gliders or all purposes with non excessive half throttle use. 6 to 17 Ni-Cd / Ni-MH cells. Can be configured using the *ips* facility.

future-45be: Identical to the **future-45bo**, but with the addition of a BEC system. That's why can be used with 6 - 12 cells.

future-45Ko: The controller for longer duration half throttle as used in sport models, aerobatic models or ducted fan models. Batt. range 6 - 17 cells; finned heat-sink; *ips*.

future-45/90Wo: The special controller for boats. Splash water protection. Cooling plate with tubes. 6/7-17 cells, *ips-car/boat*.

future-45He/Ho: Controller for helicopters with long duration initial softstart. 6-10 Ni-Cd / Ni-MH cells (...**He**), up to 17 cells (...**Ho** version); cooling ribs; fixed stick positions for neutral and full throttle. Normal speed controller and constant rpm use. Autorot. use.

future-58bo: This version can be used with 7 to 17 Ni-Cd cells in any model where the capacity of the 45A version is marginal, and where the 90A type would represent a sledgehammer to crack a nut. With its improved efficiency it is also a good choice in models where cooling can be problematic. The intended applications therefore include small hotliners and small ducted-fan models. Can also be configured using the *ips* facility.

future-58Ce/Co: the special controller for 10th scale cars. 6-10 Ni-Cd / Ni-MH cells. *ips-car/boat* (Fixed stick travel, learning neutral point; proportional brake/no brake); cooling fins.

future-70Po: The special controller made for pylon racers. Full throttle use with 7-10 Ni-Cd cells. Extra lightweight, short and low. Fixed stick travels; brake cannot be disabled.

future-90Fo: The thoroughbred speed controller for 10-cell glider competition work. Can be used with 7 - 17 cells. Fixed stick travels; brake cannot be disabled.

future-111Fo: For those who require even more than 90 A in 10-cell competition work. Can be used with 7 - 17 cells. Fixed stick travels; brake cannot be disabled.

High voltage types:

future-35bo: The controller for high cell numbers, for example as used in ducted-fan models. Battery range

16 - 30 cells; finned heat-sink; *ips*.

future-35Ho: Controller for helicopters with long duration initial softstart. 16-30 Ni-Cd / Ni-MH cells; cooling ribs; fixed stick positions for neutral and full throttle. Normal speed controller and constant rpm use. Autorotation use.

future-55bo: The high-current controller for high cell numbers. Battery range 16 - 30 cells; finned heat-sink; *ips*.

future-55Wo: The high-current controller for high cell numbers. Battery range 16 - 30 cells; finned heat-sink; *ips*.

future-80Fo: The thoroughbred controller for 27-cell competition gliders with geared motors. Only for brief operation: 5 seconds followed by 15 seconds pause. Use with 16 - 28 cells, 1000 or 1250 mAh capacity. Fixed stick travels; brake cannot be disabled; heat-sink; 72 FETs. 3 motor-modi, see section 9.3.4.

Highlights common to all units:

Ultra-small, ultra-light units. A crucial point for all modellers who require max. performance combined with minimum weight.

Better than 250-step resolut. over the whole control range for extremely fine speed control.

Controllers work reliably right down to the last scrap of energy in the battery pack.

"**Auto-arm**" function and "power on reset".

"**ips**" (intelligent programming system) with no pots! The speed controller automatically configures itself every time to the stick travel when you switch your receiver on respectively you connect your battery pack. The brake can also be disabled in the same way if required.

"*ips*" also includes a special setup variant for geared motor systems. Fixed stick travel between braking point and full-throttle point, softstart for throttle and brake. It is normally essential to apply full-throttle at the start of the flight. This variant only learns one stick position (brake point) when in use. Fine-tuning the system to match the transmitter's stick travel is still possible, but must be done by adjusting the travel at the transmitter.

During the configuration process the motor acts as a loudspeaker to give you audible confirmation of the procedure.

Naturally all **future** are suitable for use in model boats provided that it is protected from contact with water by our water shielding conformal coating.

Caution: V03 of the future...bo controller analyses the motor at initial start-up as soon as the operating voltage is present. This ensures that your motor will almost certainly start without a problem even when fitted with too large a propeller (motor overloaded) or when run with an incorrect cell count (e.g. 27-cell motor with 10 cells). For this reason it is essential that you check the load current: the maximum permissible motor current must not be exceeded at full throttle!

4 Protective circuits

Note: the monitor circuits are effective, but they cannot detect every possible operating condition.

Temperature monitor:

The temperature monitor switches off the motor. You can reset the unit using the "auto-arm" function (throttle stick to stop for about 2 sec.)



If the motor windings are short-circuited the temperature monitor reacts too slowly to prevent damage. Switch the motor off immediately to avoid permanent damage to the speed controller.

Voltage monitor:

As soon as the voltage of the drive battery falls back to the 5V threshold the motor is throttled back.

If the situation which caused the controller to throttle back continues for more than a short time, the unit switches the motor off.

Of course, you can re-start the motor again briefly by moving the throttle stick back to "stop" for about 2 seconds to re-arm the system.

If you use a *future* with opto-coupler you retain full control of the model until the receiver battery is flat;

if you use a *future* with BEC system the power system and the model remain fully controllable until the last usable energy in the flight pack is exhausted. We can not predict how long you can still control your model with the residual battery charge as this depends on many parameters such as the number of cells in the pack, the cell type, actual motor current and the way you control your model. The only solution is for you to time the period yourself with the model on the ground. If the voltage monitor trips, i.e. the motor starts to throttle back without your intervention, you should stop the motor at once with the throttle stick in any case so that you have the maximum possible reserve of power.

Current monitor:

Our *future* controllers feature a current

monitor circuit which trips when the current rises above the specified maximum value. If the motor is stalled, the motor is throttled back. This means, that a motor which draws an excessive current will never reach full-throttle, and the current may stay below the specified maximum value. If *future* is some seconds in current limiting mode, it will disarm itself (switching off the motor).

Maximum speed monitor:

If maximum rotational speed of the motor will exceed, *future* throttles down. In this state do not use longer then 1 second.

future bo or ko types cut off instantly.

Because of this: Do not run motor without airscrew.

Minimum speed monitor:

To ensure that the controller detects the rotor position reliably, this series of *future* types sets a defined minimum rotational speed. If the rotor speed falls below this value continuously, the controller switches the motor off. You can over-ride the reset with the "auto-arm" function (throttle stick to stop for about 2 sec). This protective function can cause the motor to be reluctant to start up if its torque limit is exceeded. If you are using one of the ...bo types with V03 software the only time you may notice this is when you first start the motor after changing the battery. In this case a propeller one step smaller in diameter must be used. If this should happen, check that the maximum permissible motor current is not exceeded.

Receiver signal monitor:

If the receiver signal fails, or the signal is longer or shorter than the usual range of values, the smart controller reverts to hold mode for few seconds before switching to disarmed mode.

Reverse polarity protection:



Watchdog:

If this circuit is tripped the speed controller stops working briefly and then reverts to normal operation.

These speed controllers are not protected against reversed polarity!

5 Monitor displays

The **future** is fitted with LEDs to indicate its operating status „disarmed“, „neutral“ or „brake enabled“.

However, when the unit is being configured

the set stick end-points are (in dependence of the used **future**-type or ips-mode) confirmed by a beep from the motor or a barely perceptible "blip" in full-throttle position when normal using with activated brake.

6 Installation, connections

Installing in the fuselage:

Velcro (hoop and loop) tape is the ideal method of mounting the controller in the fuselage. Do not pack the **future** in foam as this may lead to a heat build-up in the controller.

Receiver connection:

Connect the receiver cable attached to the **future** to the receiver servo output corresponding to the throttle stick on the transmitter (or a switch if that is your preference).

The **future** receives its control signal via this receiver socket.

If you use a **future** with BEC system, power is supplied to the receiver via the same cable.

Check regularly especially in this case that the receiver cable is undamaged and firmly seated at the **future**.

On no account connect a separate receiver battery or an electronic battery switch (two receiver batteries), as this may cause damage to the speed controller.

Length of connecting cables:

The cables to the flight battery and - in particular to the motor - should be kept as short as possible. Long cables tend to act as aerials and radiate interference; they also add unnecessary weight. See also section 2.

Power-connection battery <--> future:

It is essential to use **polarized** gold-plated-contact connectors - fitting any other type of connector invalidates the warranty.

Connectors which do not have a polarised insulator can be made safe (i.e. polarised) by soldering the **future's** positive battery wire to a socket, and the **future's** negative wire to a plug. **We** recommend that you choose your connectors from our selection in Section 8.

Power-connection future <--> motor:

Cut down the existing motor cables to a length of **no more than 10 cm**. Locate the cables with the pp35 plugs supplied with the controller (plugged into the **future**), and solder them to the motor cables. See separate sheet (page 1) for details of cable configuration. **Avoid** pulling on the motor cables; we recommend that you secure the three motor plugs with glass-reinforced tape to prevent them being pulled out.

9.3.8 Conversion to and from brushed motor mode

The **future ...bo** series can be used to control conventional motors at up to 2/3 of the controller's nominal current. These motors must be connected to the outer two sockets marked Motor.

To re-configure the controller for brushless or brushed motor, the motor should be connected.

1. Disconnect flight battery
2. Connect prog-adapt-2/3 cable between receiver cable (attached to the future), and receiver
3. Switch receiver on (switch BEC on)
4. Connect flight battery and wait about 5 seconds (Version 1...4: 10 seconds)
5. The motor now beeps continuously: (type of motor toggles in every re-configuration process)
 3 beeps, pause, **3** beeps, pause ... = brushless motor (**three** wires) **or**
 2 double-beeps, pause, **2** double-beeps, pause ... = brushed motor (**two** wires)
6. Disconnect flight battery
7. Remove prog-adapt-2/3 cable.

7 Legal matters

7.1 Warranty conditions

All **schulze** products are 100% dynamically tested by using a battery and a motor. We do not simulate tests.

If your unit develops a problem, please return it to **schulze** or to the importer. Include a description of the problem. Please be careful and precise, and list the battery voltage and capacity, motor type, conditions under which failure occurred etc. A note saying "doesn't work" does not help us much, and it may lead to wasted time in troubleshooting. Before returning the unit for repair, please test it "one more time" carefully. If we find that the controller is operating correctly, whether it is under warranty or not, we will make a charge for our lost time.

Warranty claims are processed according to our current General Conditions of Business, which are printed in our catalogue.

One further note:

If a problem arises with a schulze device, send it straight back to us or our authorized representative (see catalogue); don't attempt to repair it!

This allows us to repair it as quickly as possible, as we can detect warranty defects without any doubt and thus keep costs low. You can also be certain that we will fit genuine replacement parts which are a perfect match to your device. (Very few hobby shops are equipped to analyze and repair surface-mount printed circuit boards.)

We reserve the right to refuse repair to units which have been modified or "improved" by unauthorized "experts".

You also have the comfort of a properly repaired unit with a renewed warranty. The warranty period of repaired devices is applicable only to the repair. This period is shorter than the warranty period of a new product (See general conditions of business).

7.2 Liability limits / compensation

We at Schulze Elektronik GmbH are unable to monitor methods of installation and operation, and have no control over how you fit, use and maintain the devices we produce. For this reason we accept no liability for loss,

damage or costs which arise from the incorrect or incompetent use of our products, or are connected with that use in any way.

In so far as the law allows, our obligation in respect of compensation, regardless of the legal grounds, is limited to the invoice value of that quantity of goods which was immediately involved in the event which caused the damage. This does not apply if legally binding regulations oblige us to accept unlimited liability in a particular case, or if deliberate or gross negligence can be proved on our part.

7.3 CE certification

The products described in this manual are manufactured in accordance with all specific and mandatory European CE guidelines:

EMI 89/336/EEC, 91/263/EEC and 92/31/EEC.

The products have been tested according to the following norms:

EMI-emissions: EN 50 081-1:1992

**EMI-resistance: EN 50 082-1:1992 or
EN 50 082-2:1995**

The design and construction of our products comply with the requirements for safe operation.

EMI emissions were tested under realistic conditions, i.e. using suitable motors close to the maximum allowed currents. The use of resistors instead of motors do not create maximum emission levels.


Further testing is carried out to ensure adequate EMI resistance against emissions from other apparatus. The RF signals used for these tests are similar to those produced by mobile telephones and RC transmitters.

We wish to point out again that our products are tested under realistic conditions for the most dangerous scenario: exposed to the field of a powerful transmitter, the motor must not start while you are working on the model.

Problems involving our products are most likely caused by unsuitable combinations of radio components or improper installations.

8 Connector systems and mounting instructions

8.1 3.5 mm gold-contact connector system (pp35); max. load > 80A




Caution: remove locating lug from battery cable. Do not remove lug from any cables attached to controllers or charge leads!

Manufacturer's information: the **pp35** plug is very short, and this presents the danger that the spring contact could lose its resilience due to excessive heat build-up during the soldering process. You can side-step the problem by keeping the temperature below 200°C as follows: either remove the contact carefully before soldering, or simply push the plug into a piece of wet fine-grain sponge for soldering, or plug it in a 3.5 mm hole of a copper-block.

Fit the connectors in the order shown above; the contacts are pressed in as follows:

- a. Place plastic sleeve vertically on table, grip end up.
- b. Push contact down into sleeve.
- c. Place 2.5mm wide screwdriver blade on top of cable solder joint inside sleeve.
- d. Tap screwdriver to press contact into sleeve until latch engages.


8.2 4 mm gold-contact connector system (CT 4, also CT 2); max. load > 80A



Fit the connectors in the order shown above; the contacts are pressed in as follows:

- a. Rest plastic sleeve on vice jaws with cables hanging down.
- b. Close vice jaws until cables are just free to move.
- c. Fit plug into socket and tap into sleeve until latch engages.
- d. Fit socket onto plug and tap into sleeve until latch engages.


8.3 MPX gold-contact connector system (green or red); max. load ~30A



Fit the connectors in the order shown above; the contacts are soldered as follows:

- To center the contacts fit plug and socket together before soldering.
- Tin all 6 exposed contacts of plug or socket.
- Fit cable end into triangle of contacts, solder to all three contacts.
- Position heat-shrink sleeve and shrink over joint.

8.4 2,0 / 2,5 mm gold-contact connector system; max. load ~30A



Fit the connectors in the order shown above; the contacts are pressed in as follows:

- Place plastic sleeve vertically on table, grip end up.
- Push contact down into sleeve.
- Place 2.5mm wide screwdriver blade on top of cable solder joint inside sleeve.
- Tap screwdriver to press contact into sleeve until latch engages.

9 Initial use

9.1 ips, the intelligent programming system

for configuring the *future* to suit your application

The *ips* reflects the initial set-up procedure used with our speed controllers until recently, i.e. the process of adjusting the braking point with the help of a trim pot. For any normal application with an EMF brake (for a folding propeller) the start-up procedure is entirely conventional: throttle stick to "motor stopped", switch first transmitter-, then receiver on, hold model in launch position, apply full throttle, launch.

The controller has to be adjusted to match the stick travel of your transmitter - a procedure we term "configuration" - and with these units the process is fully automatic. The brake point and the full throttle point must be configured in such a way that full stick travel is always available to operate the motor, as this provides the finest possible level of control. If you wish to use the controller in a model which does not require a propeller brake the procedure is slightly different (see below).

The ...Fo types do not feature user configuration facilities. The brake and full-throttle positions are pre-set and fixed.

If you have a transmitter with adjustable servo travel we recommend that you set throttle-servo to normal full travel, i.e. +/- 100%. Adjust Multiplex servo center pulse width to 1.5 ms (= -22% center).

A single beep mostly indicates that the controller is armed! When you next move the throttle stick, the motor will start running. If the *future* beeps twice when the transmitter stick is at the brake position (double beep = full-throttle position), you must disconnect the controller and operate the servo reverse facility on your transmitter, otherwise the controller would arm itself (single beep) at the full-throttle setting of your transmitter and would run at full throttle with the stick at the "stopped" position - the exact opposite of what is required (Not future-80Fo).

9.2 Symbols and terminology

Stick: The throttle stick on the transmitter

Neutral position (self neutralising stick)

Idle position (position where the motor just barely runs) or stop position (brake).



Brake position or idle position

Position of the throttle stick where the motor stops or just barely runs.



Full-throttle position

100% voltage passed to the motor.



Wait (0.5 seconds)



Audible indicators:

These indicators are only audible when a motor is attached, as the motor itself acts as the loudspeaker.

Single beep










Double beep



Momentary interruption in running (inverse beep)










9.3.1 Propeller brake mode (*future*-__bo/...Ko/...be)

- a Receiver off (flight battery disconnected)
- b Set throttle stick to brake position 
- c Switch transmitter on **TXon**
- d Switch receiver on (connect flight battery) **RXon**
- e *future* confirms brake position with a single beep, and is now armed! 
- f Hold model in launch position, keep clear of danger area around propeller! 
- g Move throttle quickly to full-throttle position and ... 
... leave it there for about 1/2 second. Motor is already running - as with a conventional speed controller 
- h *future* confirms full-throttle position by interrupting the motor run very briefly - a barely perceptible "blip" 
- i The *future* is completely configured and the model can be flown 

The configured data is stored in the *future* until you disconnect the flight battery.

[*] In brushed motor mode every arm-beep is doubled (♪♪ this means that pitch is different).

9.3.2 No-brake mode (*future*-__bo/...Ko/...be)

- a Receiver off (flight battery disconnected)
- b Set throttle stick to full-throttle position 
- c Switch transmitter on **TXon**
- d Switch receiver on (connect flight battery) **RXon**
- e *future* confirms full-throttle position with a double beep 
- f Move throttle quickly to idle position and ...
... leave it there for about 1/2 second 

- g *future* confirms idle position with a single beep, and is now armed! 
- h The *future* is completely configured 
- i Place the model in the launch position. Keep clear of danger area around propeller. Open throttle in the normal way to start the flight. 








The configured data is stored in the *future* until you disconnect the flight battery.

[*] In brushed motor mode every arm-beep is doubled (🎵 this means that pitch is different).

9.3.3 Gearbox mode (*future*-__bo /...Ko/...be)

Setting the unit for a longer soft-start when throttle and brake are applied.

Full stick travel

- a Receiver off (flight battery disconnected)
- b Set transmitter stick to centre position
(technically: 1.5 +/- 0.15 ms pulse width) 
- c Switch transmitter on **TXon**
- d Switch receiver on (connect flight battery) **RXon**
- e *future* detects "gearbox mode", confirms with triple beep 
- f **only for no brake use, skip if brake is necessary:**
Move transmitter stick to full throttle position and leave it there until motor beeps twice (pulse width > 1.65 ms). 
- g Move transmitter stick quickly to brake / neutral position and leave it there for half a second.
(technically: pulse width less than 1.35 ms) 
- h *future* learns brake / neutral position, calculates full-throttle position (brake / neutral position + 0.6 ms), confirms with single beep and is now armed! 
- i The *future* is completely configured and is ready for use. 
- j Moving the transmitter stick towards full throttle starts the motor running. The model can be launched. 






The configured data is stored in the *future* until you disconnect the flight battery.



[*] In brushed motor mode every arm-beep is doubled (♪♪ this means that pitch is different).

9.3.4 future-__Fo, __Po (F5B-Sailplane & F5D-Pylon)

Fixed stick positions: brake = 1.2 ms, full throttle = 1.8 ms

- a Receiver off (flight battery disconnected)
- b Set transmitter stick to braake position
(technically: pulse width less than 1.2 ms) 
- c Switch transmitter on **TXon**
- d Switch receiver on (connect flight battery) **RXon**
- e The **future** detects brake position, confirms with beep(s), and is now armed! 
- f The **future** is completely configured and is ready for use 
- g Moving the transmitter stick towards full throttle starts the motor running 
- h The model can be taken off 

[*] Operational modes of future-70Po from version 5d:

Mode 1: Maximum efficiency at highest power and rotational speed.

Mode 2: Timing „retarded“ - use when having problems with runtime and over-current.

Mode 3: Timing „more retarded“ - when changing Kontronik to Schulze controller & same motor.

Mode 4: Timing „most retarded“ - for lowest idle current with Hacker and Lehner motors.

[*] Operational modes of high voltage future-80Fo (16-28 cells)

Mode 1: Limit 120 000 rpm P4; only for following high rpm contest motors:

HP220/20/A2P6 5:1 or 7:1 @ 24-28 cells and AVEOX 14HC06Y1 @ 24-27 cells.

Mode 2: Limit 58 000 rpm P4; future...bo programm with high rpm accelleration.

HP220/30/A3P4 5:1 and 7:1 @ 16-28 cells, HP370/30/A2 @ 16 - 28 cells

Well suited for Aveox, Hacker, Ikarus and Lehner motors, but not for mode 1 motors!

Mode 3: Limit 83 000 rpm P4; Mode for following Aveox and Kontronik-motors:

Aveox: 14HC06Y1,5 3.7:1 @ 16-28 cells, **F27** @ 16-28 cells, **1412Y2** 3.7:1 @ 16-28 cells.

Kontronik KBM: 42-30 6.7:1 @ 16-24 cells, **42-24** 5.2:1 @ 16-27 cells, **52-18** 3.7:1 @ 16-28 cells.






The conversion must be done with the prog-adapt-2/3 cable analogous to section 9.3.7:

Change of point 5: The motor beeps 1*, 2*, 3*, (4*), 1*, 2* ... continuously.

Respectively to the desired mode the prog-adapt-2/3 cable must be removed after having beeped 1-, 2- or more times. The future indicates the mode after this procedure until disconnecting the battery and later when arming the future by beeping 1 to 4 times in accordance with the mode.

9.3.5 future-58Ce/Co/Wo - car-mode (ips-car/boat)

proportional brake half stick travel, self neutralising

- **Splashproof design**
- **BEC 5.7 V / 3 A (bei __Ce Typ)**
- a Receiver off (drive battery disconnected)
- b Set transmitter stick to centre position (neutral)
(technically: 1.5 +/- 0.15 ms pulse width) 
- c Switch transmitter on **TXon**
- d Switch receiver on (connect drive battery) **RXon**
- e **future** learns neutral position,
calculates full-throttle position (neutral position + 0.3 ms) and brake position (neutral position - 0.3 ms) confirms with single beep and is now armed! 
- f The **future** is completely configured, the model can be used 
- g Moving the transmitter stick towards full throttle starts the motor running 
- h Moving the transmitter stick towards full brake slows the model proportionally 

The configured data is stored in the **future** until you disconnect the drive battery.

[*] In brushed motor mode every arm-beep is doubled (♪♪ this means that pitch is different).

Please use minimal 13 turns with 7,2 V brushed motors.

9.3.6 future-58Ce/Co/Wo - car-Mode (ips-car/boat)

unbraked

full stick travel, non self neutralising

- **Splashproof design**
- **BEC 5.7 V / 3 A (bei __Ce Typ)**
- a Receiver off (drive battery disconnected)
- b Set transmitter stick to centre position
(technically: pulse width less than 1.35 ms)
- c Switch transmitter on
- d Switch receiver on (connect drive battery)
- e **future** learns neutral position, calculates full-throttle position (neutral position + 0.6 ms pulse width), confirms with double beep and is now armed!
- f The **future** is completely configured, the model can be used
- g Moving the transmitter stick towards full throttle starts the motor running



TXon

RXon



The configured data is stored in the **future** until you disconnect the drive battery.

[*] In brushed motor mode every arm-beep is doubled (♪♪ this means that pitch is different).

Please use minimal 13 turns with 7,2 V brushed motors.

9.3.7 future-__He, __Ho (Helicopter)

Fixed stick positions: idle (off)=1,1 ms, full throttle=1,9 ms.

Note: If you are using a Graupner RC system this equates to +/- 100% stick travel. If you find that you cannot arm the controller reliably, the solution is to increase servo travel to about 105%...110%. In speed regulator mode the full throttle setting on a slider should be different - according to the maximum rotational speed you require - and must not be necessarily 100%.

Important: If you are using the *future* as a normal speed controller in your helicopter, you must connect the future's servo cable to the receiver output which produces the throttle curve set on the transmitter when you operate the collective pitch control.

If you are using the future as a speed regulator (governor), you must not connect the controller to the receiver channel which produces the throttle curve. Instead connect it to a channel which is controlled directly by a slider or rotary control on the transmitter, i.e. a channel not affected every time by the collective pitch control. If you ignore this, motor speed will change every time you give a collective pitch command.

9.3.7.1 Standard controller mode

- a Receiver off (flight pack disconnected)
- b Set transmitter stick to idle position (motor off)
- c Switch on transmitter
- d Switch on Receiver (connect flight pack)
- e *future* detect idle setting, confirms with beep and is armed
- f *future* is completely configured and ready to use
- g Move the transmitter stick towards full throttle, and the motor starts running.
- h The helicopter can be flown













TXon

RXon



9.3.7.2 Speed regulator mode (constant rotor head speed)

- | | | |
|----|---|---|
| a | Receiver off (flight pack disconnected) |  |
| b2 | <u>Regulator mode 2- and 4-pole motors (low rpm):</u>
Set slider slightly above idle (motor start) position.
(in technical terms: pulse widths 1.15...1.5 ms) |  |
| b3 | <u>Regulator mode 6-, 8- and 10-pole motors (high rpm):</u>
Set slider to maximum possible pulse widths (full throttle)
(in technical terms: pulse widths 1.5 ... 1.9 ms) |  |
| c | Switch on transmitter | TXon |
| d | Switch on Receiver (connect flight pack) | RXon |
| f | future detect idle position, confirms with <u>2- or 3 beeps</u>
(according to mode) |  |
| e | Move slider to minimal possible pulse widths (motor off)
(in technical terms: pulse widths lower 1.1 ms) |  |
| f | future detect idle sitting, confirms with beep and is <u>armed</u> |  |
| g | future is completely configured and ready to use |  |
| h | Move slider in the direction of full-throttle to set the rotor speed you require (see below) |  |
| i | The helicopter can be flown |   |

Tip: To provide finer control of the pre-set rotor speed, set up the slider channel on the transmitter so that the full-throttle end-point corresponds to the maximum rotor speed you ever need (e. g. for aerobatics). You can achieve this by reducing servo travel, and/or adjusting the neutral point if necessary.

Speed ranges of armed **future**, relating to 4-pole motors:

Low rpm:	Slider at 1,15 ms =	3,966 rpm;	Slider at 1,9 ms =	28,935 rpm
High rpm:	Slider at 1,15 ms =	7,931 rpm;	Slider at 1,9 ms =	57,870 rpm

Auto-rotation: If the slider channel is moved back to minimum speed by a mixer (not to the „motor stopped“ position, but to about 1.18 ms (Graupner=80%)), the integral soft-start designed for manual speed changes is reduced to the point where an auto-rotation can be interrupted quickly by suddenly (switch, no soft start) opening the throttle again.

Under-voltage: As soon as the voltage of the drive battery is not high enough the motor is throttled back first. Later **future** is switched off.

10 Specifications

Type unit	Current [A]	Ni-Cd [cells]	Size [mm]	Weight [g]	Cable [mm ²]	Thrott. [mΩ]	Brake [mΩ]	Rot.Sp. [min ⁻¹]	Version	Special features
Common Airplane:										
<i>future-18be</i>	18/24	6-10	50*25*10	16-21	1.5	6*2	6/3	63000	1	12 FETs, BEC5V/1.5A
<i>future-25be</i>	25/33	6-10	50*25*12	18-23	1.5	6*2	6/3	63000	1	15 FETs, BEC5V/1.5A
<i>future-45bo</i>	45/60	6-17	74*24*12	25-35	2.5	2.4*2	2.4/3	63000	10	36 FETs
<i>future-45be</i>	45/60	6-12	74*24*17	32-42	2.5	2.4*2	2.4/3	63000	10	BEC 5V / 3A
<i>future-45Ko</i>	45/60	6-17	74*24*14	28-38	2.5	2.4*2	2.4/3	63000	10	36 FETs, w.cool.rips
<i>future-58bo</i>	58/77	7-17	74*24*12	25-35	2.5	1.4*2	1.4/3	63000	10	36 FETs
<i>future-35bo</i>	35/45	16-30	81*24*14	28-38	2.5	4.0*2	4.0/3	63000	10	36 FETs, w.cool.rips
<i>future-55bo</i>	55/70	16-30	81*24*19	37-50	2.5	2.0*2	2.0/3	63000	10	72 FETs, w.cool.rips
Car:										
<i>future-58Co</i>	58/77	6-10	69*24*14	27-37	2.5	1.4*2	1.4/3	63000	2	36 FETs, w.cool.rips
<i>future-58Ce</i>	58/77	6-10	69*24*17	33-43	2.5	1.4*2	1.4/3	63000	2	BEC 5.7V/3A, cool.rips
Contest (FAI):										
<i>future-90Fo</i>	90/120	7-17	74*24*16	31-50	4.0	1.2*2	1.2/3	84000	4	72 FETs
<i>future-111Fo</i>	111/148	7-17	74*24*16	31-50	4.0	0.7*2	0.7/3	84000	4	72 FETs
<i>future-80Fo</i>	80/110	16-28	81*24*19	37-50	2.5	2.0*2	2.0/3	120000	6	72 FETs, w.cool.rips
Helicopter:										
<i>future-20He</i>	20/33	6-8	50*25*14	20-25	1.5	6*2	6/3	63000	1	15FETs, BEC, cool.rips
<i>future-45Ho</i>	45/60	6-17	74*24*14	28-38	2.5	2.4*2	2.4/3	63000	1	36 FETs, w.cool.rips
<i>future-45He</i>	45/60	6-10	74*24*17	34-44	2.5	2.4*2	2.4/3	63000	1	BEC 5V/3A, m.R.-Kk
<i>future-35Ho</i>	35/45	16-30	81*24*14	29-39	2.5	4.0*2	4.0/3	63000	1	36 FETs, w.cool.rips
Boat (Water):										
<i>future-45Wo</i>	56/65	6-17	74*24*18	37-51	2.5	2.4*2	2.4/3	63000	2	36 FETs, w.cool.tubes
<i>future-90Wo</i>	105/130	6-17	74*24*23	43-62	4.0	1.2*2	1.2/3	63000	2	72 FETs, w.cool.tubes
<i>future-55Wo</i>	65/80	16-30	81*24*23	50-63	2.5	2.0*2	2.0/3	63000	2	72 FETs, w.cool.tubes
Pylon:										
<i>future-70Po</i>	70/120	7-10	69*24*10	21-31	2.5	1.4*2	1.4/3	84000	5	36 FETs, thin, leightw.

Weight: Excluding - including cables

Current rating: Nominal current / maximum current:

The excess current level lies above the maximum current value for each unit.

The nominal current value is the continuous current at full throttle at which the **future** can be operated when connected to a 2 Ah battery (1250 mAh for -18be, -25be, -20He, -80Fo).

Throttle, brake: Internal resistance of the MOSFETs, based on data sheet values (25°C / 10 V gate voltage). At 125°C the resistance is about 40% higher. For this reason you should always provide an effective flow of cooling air over the **future** to prevent it getting too hot.

Pulse times: General: Allowed range: 0.8 ms ... 2.5 ms, cycle time: 10 ... 30 ms.
Gearbox-mode: Brake point <1.35 ms, fixed travel brake point <-> full throttle: ~0.6 ms.
future-__Fo: Fixed brake point = 1.2 ms, fixed full throttle point = 1.8 ms.

Rotational speed: the rotational speed stated above is the limit value for a 4-pole motor (...P4). The following multiplication factors apply: P2= *2; P4= *1; P6= *0.67; P8= *0.5; P10= *0.4. The speed limiter provides some level of protection against the armature magnets of HP 220 motors flying off. Note: this speed limit is too high for the "washing machine" motor types.

BEC: The stated peak current is dictated by the maximum current value of the 5V voltage regulator; it can only flow for less than 0.5 seconds, followed by a cooling-off period.
The stated continuous current is much lower and is determined by the maximum power dissipation of the voltage regulator used in the unit ($V_{loss} = V_{battery} - 5V$ BEC-voltage).

Pay attention when connecting micro-servos: the current consumption is mostly 2...3 times higher than the current of the Graupner C341 servo! The BEC System can be overloaded by temperature when using more than 8 cells and more than 3 servos! Power dissipation ~3.0W (i.e. at 14 V = 333 mA continuous current)

Pulse frequency: up to about 10 kHz for the ...bo types, up to about 20 kHz for the ...Fo types.
The higher pulse frequency of the ...Fo controller types provides improved behaviour under acceleration, but leads to greater heat build-up in the part-load range.

Soft-start: the soft-start feature on throttle and brake is not the same for the standard versions and the FAI versions; it is matched to the requirements of each application (FAI = short).

Temperature: Overtemperature threshold approximately 110°C.

Note: If you have been using a sensor-controlled speed controller, you may find that now your motor's maximum speed is different when you use the **future**. The timing of sensor-equipped motors is set for a particular rotational speed and a particular load (similar to the advance setting of an internal combustion engine's timing), but the **future** automatically optimises the timing for maximum efficiency under all load conditions. **This** means that the timing does not depend on the position of the speed sensors as dictated by the mechanical design, nor on the accuracy with which they are installed. The net result is that you may find that the maximum rotational speed of your motor is higher - combined with higher current; or lower - combined with lower current. **For** this reason it may prove necessary to experiment with new propeller sizes when you make the switch to a sensorless controller.

